

Supplementary information for EU Devices in the LoRaWAN® Showcase catalogue. Version 1.0

Version of Questionnaire form from the Customer/ Device Manufacturer

Version	Date	Author	Update
1.0	03.08.2020	Andres Ramirez	Initial release from manufacture

Supplementary Information on certified device

1 Supplementary information	
1.1 Manufacturer or Brand name	Swisscom (Schweiz) AG
1.2 Website	www.swisscom.ch/iot
1.3 Sales / Marketing contact person, email:	IoT.SPOC@swisscom.com
1.4 Technical contact person, email:	Support.LPN@swisscom.com
1.5 Commercial Product name	Multisense
1.6 Product code used when ordering / article number	LPN Multisense
1.7 Product Version : Hardware version: Firmware version:	REV03 V02.00.0000
1.8 In what countries is the product available	Switzerland, others on request
1.9 What date was / is the market introduction for this device / product?	9.2020
1.10 Is the device already working on a public LoRaWAN network. If yes specify at which public operator, country and number of deployed devices on that network:	<input checked="" type="checkbox"/> Yes: <input type="checkbox"/> No Swisscom, Switzerland, 70
1.11 What functionality does the device provide and which sensor(s) does it contain?	Use case: Smart Office applications Short behavior description: Configuration over the air for event triggers and parameters to be sent in the uplink
1.12 Accuracy & resolution for every sensor or measurement made by the device	
Name: sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range	SHT31-DIS-F Typ. 0.2°C (From 0 to 90°C) / Typ. 2 %RH 0.01 °C / 0.5 %RH Temperature / Humidity Same as working range
Name: sensor accuracy (incl. unit): +/- resolution (incl. unit):	LIS2DH12 40 mg offset accuracy 4 mg

measurement parameter: measurement range Name: sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range Name: sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range Name: sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range	Linear acceleration -2 g to 2 g on X, X and Z-axis
1.13 Uplinks are: Periodic: Period: Explanation: Keep alive message period: Event triggered how:	<input checked="" type="checkbox"/> 1x daily Periodically or per external sensor events (ACC, REED, BUTTON, TEMP, HUM)
1.14 Parameter configuration of device (e.g. transmission or measurement interval, threshold levels, etc.)	<input checked="" type="checkbox"/> Remotely: <input checked="" type="checkbox"/> Over-the-air with LoRaWAN data downlinks <input type="checkbox"/> Specify if other: <input type="checkbox"/> Locally: <input type="checkbox"/> Via CLI: specify type of connector: <input type="checkbox"/> Via NFC: <input type="checkbox"/> Specify if other:
1.15 Does the application server send downlinks to the devices?	<input checked="" type="checkbox"/> Yes: (why/how often/typical size) CONFIG, INFO, REJOIN DLs <input type="checkbox"/> No
1.16 Operating temperature of device - x °C to + x °C	Minimum 0 °C Maximum 60 °C
1.17 Is the payload structure available for decoding?	<input checked="" type="checkbox"/> Yes: <input type="checkbox"/> No Please attach the payload structure (+example of decoded payload)
1.18 Is there a decode-API available	<input type="checkbox"/> Yes: <input checked="" type="checkbox"/> No Please attach the API documentation
1.19 Is the firmware upgradeable and how?	<input type="checkbox"/> Yes: (how)
1.20 How can the device be reset to factory default settings?	Device can be reset with BUTTON

1.21 How can the device be forced to re-initiate the join procedure?	Either BUTTON Reset, REJOIN counter or REJOIN DL
1.22 Product certifications (IP rating, ATEX, ...)	1. IP rating: 20 2. ATEX compliance: Other:
1.23 Which regulatory certifications are available (RED, CE, EMC)?	<input type="checkbox"/> RED <input checked="" type="checkbox"/> CE <input type="checkbox"/> EMC Attach proof of certification to the mail in which this document is sent to a public operator
1.24 Power Supply	<input type="checkbox"/> External power supply: connection: voltage: amperage: <input checked="" type="checkbox"/> Internal battery: battery type: HCB CP502440 chemical composition: LiMnO2 Battery self-discharge (%/year): <2% Battery shelf life: capacity: 1.2 Ah weight: 9 g rechargeable: <input type="checkbox"/> Yes: <input checked="" type="checkbox"/> No
1.25 Powering device on and off How is the device turned ON ? How is the device turned OFF ?	Device is activated by pressing the BUTTON Once active, always active
1.26 Dimensions of device (Length x width x height)	8.0 x 3.5 x 1.3 cm
1.27 Weight of full device	35 g
1.28 Mounting of device 1. How to mount? 2. How to mount for best antenna propagation	Contact Swisscom for more information Contact Swisscom for more information

2 LoRaWAN Device Information

2.1 DevEUI Range (IEEE Compliance)	From :BC9740FFFE100000 To : BC9740FFFEFFFFFF
2.2 LoRaWAN Class	<input checked="" type="checkbox"/> Class A <input type="checkbox"/> Class B <input type="checkbox"/> Class C
2.3 For Class C Device: Device Under Test restores previous RF settings at boot?	<input type="checkbox"/> Yes <input type="checkbox"/> No
2.4 In what LoRaWAN region/frequency ranges is the product available	<input checked="" type="checkbox"/> EU863-870 <input type="checkbox"/> US902-928 <input type="checkbox"/> AS923 <input type="checkbox"/> IN865-867 <input type="checkbox"/> KR920-923 <input type="checkbox"/> Other
2.5 Is the LoRaWAN test mode supported?	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No, why not
2.6 Tested and certified against which LoRaWAN Specification(s)	<input type="checkbox"/> V1.0 <input type="checkbox"/> V1.0.1 <input checked="" type="checkbox"/> V1.0.2 revB <input type="checkbox"/> V1.0.3 <input type="checkbox"/> V1.1.x <input type="checkbox"/> Other :
2.7 Link to document on the LoRa Alliance website	Link:
<p>2.8 Which TX power is used in production devices by default?</p> <p>- if LW 1.0.2 rev A or older is used:</p> <p>- if LW 1.0.2 rev B or newer is used</p>	<p> <input type="checkbox"/> TXPower 0 (20dBm) <input type="checkbox"/> TXPower 1 (14dBm) <input type="checkbox"/> TXPower 2 (11dBm) <input type="checkbox"/> TXPower 3 (8dBm) <input type="checkbox"/> TXPower 4 (5dBm) <input type="checkbox"/> TXPower 5 (2dBm) <input type="checkbox"/> other TXPower (dBm) </p> <p> <input checked="" type="checkbox"/> TXPower 0 (MaxEIRP) <input type="checkbox"/> TXPower 1 (MaxEIRP-2dB) <input type="checkbox"/> TXPower 2 (MaxEIRP-4dB) <input type="checkbox"/> TXPower 3 (MaxEIRP-6dB) <input type="checkbox"/> TXPower 4 (MaxEIRP-8dB) <input type="checkbox"/> TXPower 5 (MaxEIRP-10dB) <input type="checkbox"/> TXPower 6 (MaxEIRP-12dB) <input type="checkbox"/> TXPower 7 (MaxEIRP-14dB) </p> <p> <input type="checkbox"/> other TXPower (Max EIRP : dB) </p>

<p>2.9 Which TX powers are supported by the device in production</p> <p>- if LW 1.0.2 rev A or older is used:</p> <p>- if LW 1.0.2 rev B or newer is used</p>	<p><input type="checkbox"/> TXPower 0 (20dBm)</p> <p><input type="checkbox"/> TXPower 1 (14dBm)</p> <p><input type="checkbox"/> TXPower 2 (11dBm)</p> <p><input type="checkbox"/> TXPower 3 (8dBm)</p> <p><input type="checkbox"/> TXPower 4 (5dBm)</p> <p><input type="checkbox"/> TXPower 5 (2dBm)</p> <p><input type="checkbox"/> other TXPower (dBm)</p> <p><input checked="" type="checkbox"/> TXPower 0 (MaxEIRP)</p> <p><input type="checkbox"/> TXPower 1 (MaxEIRP-2dB)</p> <p><input type="checkbox"/> TXPower 2 (MaxEIRP-4dB)</p> <p><input type="checkbox"/> TXPower 3 (MaxEIRP-6dB)</p> <p><input type="checkbox"/> TXPower 4 (MaxEIRP-8dB)</p> <p><input type="checkbox"/> TXPower 5 (MaxEIRP-10dB)</p> <p><input type="checkbox"/> TXPower 6 (MaxEIRP-12dB)</p> <p><input type="checkbox"/> TXPower 7 (MaxEIRP-14dB)</p> <p>(Max EIRP : dB)</p>
<p>2.9 Which LoRaWAN Specification is currently supported on the production devices?</p>	<p><input type="checkbox"/> V1.0</p> <p><input type="checkbox"/> V1.0.1</p> <p><input type="checkbox"/> V1.0.2 revA</p> <p><input checked="" type="checkbox"/> V1.0.2 revB</p> <p><input type="checkbox"/> V1.0.4</p> <p><input type="checkbox"/> V1.1.x</p> <p><input type="checkbox"/> Other:</p>
<p>2.10 Will you re-certify your device when a new major LoRaWAN specification version is released</p>	<p><input checked="" type="checkbox"/> Yes.</p> <p><input type="checkbox"/> No, why :</p>
<p>2.11 Has Interoperability prequalification testing been done?</p>	<p><input checked="" type="checkbox"/> Yes.</p> <p><input type="checkbox"/> No, why :</p> <p>Which Network Servers</p> <p><input type="checkbox"/> Actility</p> <p><input type="checkbox"/> Loriot</p> <p><input type="checkbox"/> TTI</p> <p><input checked="" type="checkbox"/> Other: Specify: Swisscom</p> <p>Please attach all the test reports.</p>
<p>2.12 Is Activation Type OTAA the default</p>	<p><input checked="" type="checkbox"/> Yes.</p> <p><input type="checkbox"/> No, why :</p>
<p>2.13 For OTAA, is AppKey unique for each device?</p>	<p><input checked="" type="checkbox"/> Yes.</p> <p><input type="checkbox"/> No.</p>

<p>2.14 Is ADR implemented? Recommendation: ADR should always be activated. Exceptions can be made for moving devices but will need to be explained.</p>	<p><input type="checkbox"/> Activated <input type="checkbox"/> Deactivated, why : <input checked="" type="checkbox"/> Configurable by user (recommendation: Activated by default) <input type="checkbox"/> Mixed, explain:</p>
<p>2.15 What values did you implement for: - ADR_ACK_LIMIT: - ADR_ACK_DELAY:</p>	<p>64recommended value: 64 32recommended value: 32</p>
<p>2.16 Do you use unconfirmed and/or confirmed uplinks and what is the data rate, timing and power back off algorithm? Upon reception of a confirmed downlink message, is the next uplink sent immediately after the downlink ?Answers (radio buttons)</p>	<p><input type="checkbox"/> unconfirmed <input type="checkbox"/> confirmed, when and why: <input checked="" type="checkbox"/> Both, which is used when and why: External events can be configured to send confirmed ULs Data rate, timing and power back-off algorithm (only if you use confirmed uplinks): Runs LoRaMAC's native ADR algorithm <input type="checkbox"/> Yes. <input checked="" type="checkbox"/> No, why : Battery powered, MAC commands answered with next UL</p>
<p>2.17 Is the device doing a periodical rejoin? (only for OTAA)</p>	<p><input checked="" type="checkbox"/> Yes (frequency): Per default, every 10000 ULs <input type="checkbox"/> No. Why? How to trigger a rejoin?</p>
<p>2.18 Is the first join request sent on SF12?</p>	<p><input checked="" type="checkbox"/> Yes. <input type="checkbox"/> No, why: Explain the JoinRequest sequence if no JoinAccept is received - data rate, timing and power back-off algorithm. Rejoin is generated with next UL attempt, respecting the LoRaMAC's native duty cycle control</p>
<p>2.19 On what SF and power setting is the first uplink (after join procedure) done?</p>	<p>SF: 12 TXPower: TXPower 0 (MaxEIRP)</p>
<p>2.20 Are you doing periodically reset of Uplink frame counter?</p>	<p><input type="checkbox"/> Yes (frequency/why): <input checked="" type="checkbox"/> No.</p>
<p>2.21 If LoRaWAN 1.0.x, DevNonce behaviour :</p>	<p><input checked="" type="checkbox"/> Based on a random value <input type="checkbox"/> Monotonically increasing never-wrapping counter</p>
<p>2.22 Uplink DataRate (0-7 supported)</p>	<p>Min: 0 Max: 5</p>
<p>2.23 RX1 Data Rate Offset</p>	<p><input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:</p>
<p>2.24 RX1 Delay</p>	<p><input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:</p>

2.25 RX2 Data Rate	<input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:
2.26 RX2 Frequency	<input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:
2.27 RX1 Delay on JoinRequest (OTAA devices only)	<input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:
2.28 Mobility Profile (how your device moves)	<input checked="" type="checkbox"/> Near static <input type="checkbox"/> Walking speed <input type="checkbox"/> Vehicle speed <input type="checkbox"/> Random
2.29 Frame Counters Up To 32-bits	<input checked="" type="checkbox"/> Frame counter-up <input type="checkbox"/> Frame counter-down
2.30 Which MAC commands does the device support	<input checked="" type="checkbox"/> LinkCheckReq / LinkCheckAns <input checked="" type="checkbox"/> TXParamSetupReq / TXParamSetupAns <input checked="" type="checkbox"/> LinkADRRReq / LinkADRAns <input checked="" type="checkbox"/> DutyCycleReq / DutyCycleAns <input checked="" type="checkbox"/> RXParamSetupReq /RXParamSetupAns <input checked="" type="checkbox"/> DevStatusReq / DevStatusAns <input checked="" type="checkbox"/> NewChannelReq / NewChannelAns <input checked="" type="checkbox"/> TXTimingSetupReq / TXTimingSetupAns
2.31 LoRaWAN Stack Type (optional)	<input checked="" type="checkbox"/> Semtech/Stackforce <input type="checkbox"/> Semtech/Stackforce with modifications <input type="checkbox"/> IBM <input type="checkbox"/> IBM with modifications <input type="checkbox"/> Proprietary- Other, name it:
2.32 LoRaWAN Stack Version (optional)	V4.4.4
2.33 LoRa Radio Hardware (optional)	<input type="checkbox"/> Proprietary: SX chip used: <input checked="" type="checkbox"/> LoRaWAN Modem/Module: Manufacturer: Murata Part Number: CMWX1ZZABZ-078 Firmware revision:
2.34 Multicast support (optional)	<input type="checkbox"/> Yes: Multicast DevAddr: Multicast AppSKey: Multicast NwkSKey: Payload: Port: <input checked="" type="checkbox"/> No.

3 Radio Frequency Information

3.1 Type of Antenna	<input type="checkbox"/> Wire <input type="checkbox"/> PCB <input type="checkbox"/> External <input checked="" type="checkbox"/> Other: (which type) Fractus Antenna, SMD
3.2 Antenna gain [dBi or dBd]	1.6dBi or dBd
3.3 Did you measure and take into account the loss between the modem and the antenna?	<input checked="" type="checkbox"/> Yes, 0.22 dB loss <input type="checkbox"/> No, why:
3.4 For LW 1.0.2 rev A or older devices: which TXPower setting should be used on the network for your device*:	<input type="checkbox"/> TXPower 0 (20dBm) <input type="checkbox"/> TXPower 1 (14dBm) <input type="checkbox"/> TXPower 2 (11dBm) <input type="checkbox"/> TXPower 3 (8dBm) <input type="checkbox"/> TXPower 4 (5dBm) <input type="checkbox"/> TXPower 5 (2dBm) <input type="checkbox"/> other txpower (dBm)
3.5 Did you calibrate your device with the antenna gain and measured loss in between the chipset and antenna? This so that your device emits with maximal power when using TXPower 1 for LW 1.0.2 rev A or older devices (= 14dBm) and TXPower 0 for LW 1.0.2 rev B or newer devices (= MaxEIRP or 16.15dBm EIRP)*.	<input checked="" type="checkbox"/> Yes, 0.22 dB loss <input type="checkbox"/> No, why:

4 Battery and TX Power Information

Please indicate if you do not want Section 4 displayed on the LoRa Alliance Website Yes
 If yes please supply contact details for the operators to request the information for Section 4

<p>4.1 Battery consumption of the device (including modem, sensors and all other electronics)</p>	<p>TX current: 50 mA RX current: 11 mA Idle time current: 0.001 mA</p>																																				
<p>4.2 Estimated battery life in years based on the number of transmissions (including sensor readings) at SF7, SF10 & SF12 with your battery self-discharge and aging over time taken into account.</p> <p>Assumptions:</p> <ul style="list-style-type: none"> - Product shelf life before use: Maximum 1 year. - At an environment temperature of 20°C. - LoRaWAN specification used for battery life calculation: - TX power setting (txpower) used for battery life calculation: - Payload size used for battery life calculation (should be average payload size of production device): - Additional assumptions or comments on battery life (Typical usage 	<table border="1"> <thead> <tr> <th colspan="4">Battery life in years</th> </tr> <tr> <th>Transmission Periodicity (transmissions/day)</th> <th>SF7</th> <th>SF10</th> <th>SF12</th> </tr> </thead> <tbody> <tr> <td>144</td> <td>4.67</td> <td>1.11</td> <td>0.30</td> </tr> <tr> <td>96</td> <td>5.92</td> <td>1.59</td> <td>0.44</td> </tr> <tr> <td>48</td> <td>8.09</td> <td>2.82</td> <td>0.84</td> </tr> <tr> <td>24</td> <td>9.91</td> <td>4.57</td> <td>1.56</td> </tr> <tr> <td>12</td> <td>>10</td> <td>6.62</td> <td>2.69</td> </tr> <tr> <td>4</td> <td>>10</td> <td>9.46</td> <td>5.25</td> </tr> <tr> <td>1</td> <td>>10</td> <td>>10</td> <td>8.16</td> </tr> </tbody> </table> <p> <input type="checkbox"/> LW1.0.1 <input type="checkbox"/> LW1.0.2 revA <input checked="" type="checkbox"/> LW1.0.2 revB <input type="checkbox"/> Other : </p> <p> <input type="checkbox"/> LW1.0.1 <input type="checkbox"/> LW1.0.2 revA <input checked="" type="checkbox"/> LW1.0.2 revB <input type="checkbox"/> Other : </p> <p>30 bytes</p> <p>BUTTON, TEMP & HUM ON. TEMP & HUM history option ON. Everything else off</p>	Battery life in years				Transmission Periodicity (transmissions/day)	SF7	SF10	SF12	144	4.67	1.11	0.30	96	5.92	1.59	0.44	48	8.09	2.82	0.84	24	9.91	4.57	1.56	12	>10	6.62	2.69	4	>10	9.46	5.25	1	>10	>10	8.16
Battery life in years																																					
Transmission Periodicity (transmissions/day)	SF7	SF10	SF12																																		
144	4.67	1.11	0.30																																		
96	5.92	1.59	0.44																																		
48	8.09	2.82	0.84																																		
24	9.91	4.57	1.56																																		
12	>10	6.62	2.69																																		
4	>10	9.46	5.25																																		
1	>10	>10	8.16																																		

<p>4.3 Which TX power setting (TXPower) was used in the RF test?</p> <p>- If LW 1.0.2 rev A or older device:</p> <p>- If LW 1.0.2 rev B or newer device:</p>	<p><input type="checkbox"/> TXPower 0 (20dBm)</p> <p><input type="checkbox"/> TXPower 1 (14dBm)</p> <p><input type="checkbox"/> TXPower 2 (11dBm)</p> <p><input type="checkbox"/> TXPower 3 (8dBm)</p> <p><input type="checkbox"/> TXPower 4 (5dBm)</p> <p><input type="checkbox"/> TXPower 5 (2dBm)</p> <p><input type="checkbox"/> other TXPower (dBm)</p> <p><input checked="" type="checkbox"/> TXPower 0 (MaxEIRP)</p> <p><input type="checkbox"/> TXPower 1 (MaxEIRP-2dB)</p> <p><input type="checkbox"/> TXPower 2 (MaxEIRP-4dB)</p> <p><input type="checkbox"/> TXPower 3 (MaxEIRP-6dB)</p> <p><input type="checkbox"/> TXPower 4 (MaxEIRP-8dB)</p> <p><input type="checkbox"/> TXPower 5 (MaxEIRP-10dB)</p> <p><input type="checkbox"/> TXPower 6 (MaxEIRP-12dB)</p> <p><input type="checkbox"/> TXPower 7 (MaxEIRP-14dB)</p> <p><input type="checkbox"/> other TXPower (MaxEIRP- dBdBm)</p>
<p>4.4 Is this the same TX power setting (TXPower) used by default in production devices (before network ADR)?</p>	<p><input checked="" type="checkbox"/> Yes, TXPower (MaxEIRP)</p> <p><input type="checkbox"/> No, why:</p>
<p>4.5 Maximum ERP measured: (ERP = EIRP - 2.15 dB; LoRaWAN allows 14 dBm ERP)</p>	<p>12.9 dBm</p>
<p>4.6 TRP measured: (TRP is based on EIRP) This gives an idea about the directivity of the antenna.</p>	<p>12.9 dBm</p>
<p>3.10 TIS measured on RX1:</p>	<p>For RX1-SF12BW125 on 868.3MHz -133.4 dBm</p>
<p>3.11 TIS measured on RX2</p>	<p>For RX2-SF12BW125 on 869.525 MHz: -133.3 dBm</p>