

Supplementary information for EU Devices in the LoRaWAN® Showcase catalogue. Version 1.0

### Version of Questionnaire form from the Customer/ Device Manufacturer

Version	Date	Author	Update
1.0	2021-9-28	Edwin Chen	Initial release from manufacture

### Supplementary Information on certified device

1 Supplementary information	
1.1 Manufacturer or Brand name	DRAGINO
1.2 Website	<a href="https://www.dragino.com">https://www.dragino.com</a>
1.3 Sales / Marketing contact person, email:	sales@dragino.com
1.4 Technical contact person, email:	support@dragino.com
1.5 Commercial Product name	LoRaWAN IoT Sensor Node
1.6 Product code used when ordering / article number	RS485-LN
1.7 Product Version : Hardware version: Firmware version:	RS485-LN LSN50 RS485-UART-I2C v1.4 RS485-LN v2.0
1.8 In what countries is the product available	World Widely
1.9 What date was / is the market introduction for this device / product?	2019-Sep
1.10 Is the device already working on a public LoRaWAN network. If yes specify at which public operator, country and number of deployed devices on that network:	<input checked="" type="checkbox"/> Yes: <input type="checkbox"/> No TheThethings Network. Product used world widely. Deploy Numbers: Several Thousands.
1.11 What functionality does the device provide and which sensor(s) does it contain?	Use case: General RS485 to LoRaWAN converter  Short behaviour description: RS485 interface
1.12 Accuracy & resolution for every sensor or measurement made by the device	
	Name: sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range
	Name: sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range

<p>Name: sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range</p>	
<p>Name: sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range</p>	
<p>Name: sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range</p>	
<p>1.13 Uplinks are: Periodic: Period: Explanation: Keep alive message period: Event triggered how:</p>	<p><input checked="" type="checkbox"/> Periodic: 20 minutes  <input checked="" type="checkbox"/> Locally: 20 minutes Interrupt pin</p>
<p>1.14 Parameter configuration of device (e.g. transmission or measurement interval, threshold levels, etc.)</p>	<p><input type="checkbox"/> Remotely: <input checked="" type="checkbox"/> Over-the-air with LoRaWAN data downlinks <input type="checkbox"/> Specify if other:  <input checked="" type="checkbox"/> Locally: <input checked="" type="checkbox"/> Via CLI: specify type of connector: TTL UART <input type="checkbox"/> Via NFC:  <input type="checkbox"/> Specify if other:</p>
<p>1.15 Does the application server send downlinks to the devices?</p>	<p><input checked="" type="checkbox"/> Yes: (why/how often/typical size) To configure device parameters. Sent in demand. Typical Size below 11 bytes <input type="checkbox"/> No</p>
<p>1.16 Operating temperature of device - x °C to + x °C</p>	<p>Minimum -40 °C Maximum 85 °C</p>
<p>1.17 Is the payload structure available for decoding?</p>	<p><input checked="" type="checkbox"/> Yes: <input type="checkbox"/> No Please attach the payload structure (+example of decoded payload)</p>
<p>1.18 Is there a decode-API available</p>	<p><input checked="" type="checkbox"/> Yes: <input type="checkbox"/> No Please attach the API documentation See LDDS75_Decoder.js</p>
<p>1.19 Is the firmware upgradeable and how?</p>	<p><input checked="" type="checkbox"/> Yes: (how) Through UART or ST Link v2</p>
<p>1.20 How can the device be reset to factory default settings?</p>	<p>Through Downlink Command or use AT Command in CLI</p>

1.21 How can the device be forced to re-initiate the join procedure?	Downlink to reset the device or press the reset button
1.22 Product certifications (IP rating, ATEX, ...)	1. IP rating: IP67 2. ATEX compliance: Other:
1.23 Which regulatory certifications are available (RED, CE, EMC)?	<input checked="" type="checkbox"/> RED <input checked="" type="checkbox"/> CE <input checked="" type="checkbox"/> EMC Attach proof of certification to the mail in which this document is sent to a public operator. <a href="#">See RED directory</a>
1.24 Power Supply	<input type="checkbox"/> External power supply: connection: voltage: amperage:  <input checked="" type="checkbox"/> Internal battery: battery type: Li-SOCI2 chemical composition: Battery self-discharge (%/year): <2% Battery shelf life: > 5 years capacity: 8500mAh weight: 52g rechargeable: <input type="checkbox"/> Yes: <input checked="" type="checkbox"/> No
1.25 Powering device on and off How is the device turned ON ? How is the device turned OFF ?	Put Jumper to power on Remove Jumper to power off
1.26 Dimensions of device (Length x width x height)	11*9*2.5 cm
1.27 Weight of full device	210 g
1.28 Mounting of device 1. How to mount? 2. How to mount for best antenna propagation	Vis screws Antenna towards Sky

2 LoRaWAN Device Information

2.1 DevEUI Range (IEEE Compliance)	From :A840410000000000 To : A84041FFFFFFFF
2.2 LoRaWAN Class	<input checked="" type="checkbox"/> Class A <input type="checkbox"/> Class B <input type="checkbox"/> Class C
2.3 For Class C Device: Device Under Test restores previous RF settings at boot?	<input type="checkbox"/> Yes <input type="checkbox"/> No
2.4 In what LoRaWAN region/frequency ranges is the product available	<input checked="" type="checkbox"/> EU863-870 <input checked="" type="checkbox"/> US902-928 <input checked="" type="checkbox"/> AS923 <input checked="" type="checkbox"/> IN865-867 <input checked="" type="checkbox"/> KR920-923 <input checked="" type="checkbox"/> Other RU864, KZ865,MA869,AU915
2.5 Is the LoRaWAN test mode supported?	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No, why not
2.6 Tested and certified against which LoRaWAN Specification(s)	<input type="checkbox"/> V1.0 <input type="checkbox"/> V1.0.1 <input type="checkbox"/> V1.0.2 revB <input type="checkbox"/> V1.0.3 <input type="checkbox"/> V1.1.x <input checked="" type="checkbox"/> Other : v1.0.4
2.7 Link to document on the LoRa Alliance website	Link:
2.8 Which TX power is used in production devices by default?  - if LW 1.0.2 rev A or older is used:          - if LW 1.0.2 rev B or newer is used	<input type="checkbox"/> TXPower 0 (20dBm) <input type="checkbox"/> TXPower 1 (14dBm) <input type="checkbox"/> TXPower 2 (11dBm) <input type="checkbox"/> TXPower 3 (8dBm) <input type="checkbox"/> TXPower 4 (5dBm) <input type="checkbox"/> TXPower 5 (2dBm) <input type="checkbox"/> other TXPower (        dBm)  <input checked="" type="checkbox"/> TXPower 0 (MaxEIRP) <input type="checkbox"/> TXPower 1 (MaxEIRP-2dB) <input type="checkbox"/> TXPower 2 (MaxEIRP-4dB) <input type="checkbox"/> TXPower 3 (MaxEIRP-6dB) <input type="checkbox"/> TXPower 4 (MaxEIRP-8dB) <input type="checkbox"/> TXPower 5 (MaxEIRP-10dB) <input type="checkbox"/> TXPower 6 (MaxEIRP-12dB) <input type="checkbox"/> TXPower 7 (MaxEIRP-14dB)  <input type="checkbox"/> other TXPower (Max EIRP :        dB)



<p>2.14 Is ADR implemented? Recommendation: ADR should always be activated. Exceptions can be made for moving devices but will need to be explained.</p>	<p><input checked="" type="checkbox"/> Activated <input type="checkbox"/> Deactivated, why :  <input type="checkbox"/> Configurable by user (recommendation: Activated by default) <input type="checkbox"/> Mixed, explain:</p>
<p>2.15 What values did you implement for: - ADR_ACK_LIMIT: - ADR_ACK_DELAY:</p>	<p>64 32</p>
<p>2.16 Do you use unconfirmed and/or confirmed uplinks and what is the data rate, timing and power back off algorithm?  Upon reception of a confirmed downlink message, is the next uplink sent immediately after the downlink ?Answers (radio buttons)</p>	<p><input type="checkbox"/> unconfirmed <input type="checkbox"/> confirmed, when and why: <input checked="" type="checkbox"/> Both, which is used when and why: Data rate, timing and power back-off algorithm (only if you use confirmed uplinks):  <input type="checkbox"/> Yes. <input checked="" type="checkbox"/> No, why : Default no, need to enable in software</p>
<p>2.17 Is the device doing a periodical rejoin? (only for OTAA)</p>	<p><input type="checkbox"/> Yes (frequency): <input checked="" type="checkbox"/> No. Why? How to trigger a rejoin? Press button or Send a downlink</p>
<p>2.18 Is the first join request sent on SF12?</p>	<p><input type="checkbox"/> Yes. <input checked="" type="checkbox"/> No, why: Save battery life Explain the JoinRequest sequence if no JoinAccept is received - data rate, timing and power back-off algorithm. The join request will start from SF7 and increase by one SF every three until SF12.</p>
<p>2.19 On what SF and power setting is the first uplink (after join procedure) done?</p>	<p>SF: 12 TXPower: 0</p>
<p>2.20 Are you doing periodically reset of Uplink frame counter?</p>	<p><input type="checkbox"/> Yes (frequency/why): <input checked="" type="checkbox"/> No.</p>
<p>2.21 If LoRaWAN 1.0.x, DevNonce behaviour :</p>	<p><input type="checkbox"/> Based on a random value <input checked="" type="checkbox"/> Monotonically increasing never-wrapping counter</p>
<p>2.22 Uplink DataRate (0-7 supported)</p>	<p>Min: 0 Max: 7</p>
<p>2.23 RX1 Data Rate Offset</p>	<p><input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:</p>
<p>2.24 RX1 Delay</p>	<p><input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:</p>
<p>2.25 RX2 Data Rate</p>	<p><input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:</p>

2.26 RX2 Frequency	<input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:
2.27 RX1 Delay on JoinRequest (OTAA devices only)	<input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:
2.28 Mobility Profile (how your device moves)	<input checked="" type="checkbox"/> Near static <input type="checkbox"/> Walking speed <input type="checkbox"/> Vehicle speed <input type="checkbox"/> Random
2.29 Frame Counters Up To 32-bits	<input checked="" type="checkbox"/> Frame counter-up <input type="checkbox"/> Frame counter-down
2.30 Which MAC commands does the device support	<input checked="" type="checkbox"/> LinkCheckReq / LinkCheckAns <input checked="" type="checkbox"/> TXParamSetupReq / TXParamSetupAns <input checked="" type="checkbox"/> LinkADRRReq / LinkADRAns <input checked="" type="checkbox"/> DutyCycleReq / DutyCycleAns <input checked="" type="checkbox"/> RXParamSetupReq /RXParamSetupAns <input checked="" type="checkbox"/> DevStatusReq / DevStatusAns <input checked="" type="checkbox"/> NewChannelReq / NewChannelAns <input checked="" type="checkbox"/> TXTimingSetupReq / TXTimingSetupAns
2.31 LoRaWAN Stack Type (optional)	<input checked="" type="checkbox"/> Semtech/Stackforce <input type="checkbox"/> Semtech/Stackforce with modifications <input type="checkbox"/> IBM <input type="checkbox"/> IBM with modifications <input type="checkbox"/> Proprietary- Other, name it:
2.32 LoRaWAN Stack Version (optional)	V1.0.4
2.33 LoRa Radio Hardware (optional)	<input checked="" type="checkbox"/> Proprietary: SX chip used: SX1276 <input type="checkbox"/> LoRaWAN Modem/Module: Manufacturer: Part Number: Firmware revision:
2.34 Multicast support (optional)	<input type="checkbox"/> Yes: Multicast DevAddr: Multicast AppSKey: Multicast NwkSKey: Payload: Port: <input checked="" type="checkbox"/> No.

**3 Radio Frequency Information**

<p>3.1 Type of Antenna</p>	<p><input type="checkbox"/> Wire  <input type="checkbox"/> PCB  <input checked="" type="checkbox"/> External  <input type="checkbox"/> Other: (which type)</p>
<p>3.2 Antenna gain [dBi or dBd]</p>	<p>2 dBi or  dBd</p>
<p>3.3 Did you measure and take into account the loss between the modem and the antenna?</p>	<p><input checked="" type="checkbox"/> Yes, 0.7 dB loss  <input type="checkbox"/> No, why:</p>
<p>3.4 For LW 1.0.2 rev A or older devices: which TXPower setting should be used on the network for your device*:</p>	<p><input type="checkbox"/> TXPower 0 (20dBm)  <input type="checkbox"/> TXPower 1 (14dBm)  <input type="checkbox"/> TXPower 2 (11dBm)  <input type="checkbox"/> TXPower 3 (8dBm)  <input type="checkbox"/> TXPower 4 (5dBm)  <input type="checkbox"/> TXPower 5 (2dBm)  <input type="checkbox"/> other txpower (        dBm)</p>
<p>3.5 Did you calibrate your device with the antenna gain and measured loss in between the chipset and antenna? This so that your device emits with maximal power when using TXPower 1 for LW 1.0.2 rev A or older devices (= 14dBm) and TXPower 0 for LW 1.0.2 rev B or newer devices (= MaxEIRP or 16.15dBm EIRP)*.</p>	<p><input checked="" type="checkbox"/> Yes, 0.7 dB loss  <input type="checkbox"/> No, why:</p>



**4 Battery and TX Power Information**

Please indicate if you do not want Section 4 displayed on the LoRa Alliance Website  Yes  
 If yes please supply contact details for the operators to request the information for Section 4

<p>4.1 Battery consumption of the device (including modem, sensors and all other electronics)</p>	<p>TX current: 150 mA                  RX current: 20 mA                  Idle time current: 0.008 mA</p>																																				
<p>4.2 Estimated battery life in years based on the number of transmissions (including sensor readings) at SF7, SF10 &amp; SF12 with your battery self-discharge and aging over time taken into account.</p> <p><b>Assumptions:</b></p> <ul style="list-style-type: none"> <li>- Product shelf life before use: Maximum 1 year.</li> <li>- At an environment temperature of 20°C.</li> <li>- LoRaWAN specification used for battery life calculation:</li> <li>- TX power setting (txpower) used for battery life calculation:</li> <li>- Payload size used for battery life calculation (should be average payload size of production device):</li> <li>- Additional assumptions or comments on battery life (Typical usage)</li> </ul>	<table border="1"> <thead> <tr> <th colspan="4">Battery life in years</th> </tr> <tr> <th>Transmission Periodicity (transmissions/day)</th> <th>SF7</th> <th>SF10</th> <th>SF12</th> </tr> </thead> <tbody> <tr> <td>144</td> <td>3</td> <td>2.5</td> <td>1.3</td> </tr> <tr> <td>96</td> <td>4</td> <td>3</td> <td>2</td> </tr> <tr> <td>48</td> <td>6</td> <td>5</td> <td>4</td> </tr> <tr> <td>24</td> <td>10</td> <td>9</td> <td>6</td> </tr> <tr> <td>12</td> <td>15</td> <td>12</td> <td>10</td> </tr> <tr> <td>4</td> <td>15</td> <td>12</td> <td>10</td> </tr> <tr> <td>1</td> <td>15</td> <td>12</td> <td>10</td> </tr> </tbody> </table> <p> <input type="checkbox"/> LW1.0.1  <input type="checkbox"/> LW1.0.2 revA  <input type="checkbox"/> LW1.0.2 revB  <input checked="" type="checkbox"/> Other : 1.0.4                 </p> <p> <input type="checkbox"/> LW1.0.1  <input type="checkbox"/> LW1.0.2 revA  <input type="checkbox"/> LW1.0.2 revB  <input checked="" type="checkbox"/> Other : 1.0.4                 </p> <p>11 bytes</p>	Battery life in years				Transmission Periodicity (transmissions/day)	SF7	SF10	SF12	144	3	2.5	1.3	96	4	3	2	48	6	5	4	24	10	9	6	12	15	12	10	4	15	12	10	1	15	12	10
Battery life in years																																					
Transmission Periodicity (transmissions/day)	SF7	SF10	SF12																																		
144	3	2.5	1.3																																		
96	4	3	2																																		
48	6	5	4																																		
24	10	9	6																																		
12	15	12	10																																		
4	15	12	10																																		
1	15	12	10																																		

<p>4.3 Which TX power setting (TXPower) was used in the RF test?</p> <p>- If LW 1.0.2 rev A or older device:</p> <p>- If LW 1.0.2 rev B or newer device:</p>	<p><input type="checkbox"/> TXPower 0 (20dBm)</p> <p><input type="checkbox"/> TXPower 1 (14dBm)</p> <p><input type="checkbox"/> TXPower 2 (11dBm)</p> <p><input type="checkbox"/> TXPower 3 (8dBm)</p> <p><input type="checkbox"/> TXPower 4 (5dBm)</p> <p><input type="checkbox"/> TXPower 5 (2dBm)</p> <p><input type="checkbox"/> other TXPower (        dBm)</p> <p><input checked="" type="checkbox"/> TXPower 0 (MaxEIRP)</p> <p><input type="checkbox"/> TXPower 1 (MaxEIRP-2dB)</p> <p><input type="checkbox"/> TXPower 2 (MaxEIRP-4dB)</p> <p><input type="checkbox"/> TXPower 3 (MaxEIRP-6dB)</p> <p><input type="checkbox"/> TXPower 4 (MaxEIRP-8dB)</p> <p><input type="checkbox"/> TXPower 5 (MaxEIRP-10dB)</p> <p><input type="checkbox"/> TXPower 6 (MaxEIRP-12dB)</p> <p><input type="checkbox"/> TXPower 7 (MaxEIRP-14dB)</p> <p><input type="checkbox"/> other TXPower (MaxEIRP-        dBdBm)</p>
<p>4.4 Is this the same TX power setting (TXPower) used by default in production devices (before network ADR)?</p>	<p><input checked="" type="checkbox"/> Yes,</p> <p><input type="checkbox"/> No, why:</p>
<p>4.5 Maximum ERP measured: (ERP = EIRP - 2.15 dB; LoRaWAN allows 14 dBm ERP)</p>	<p>14 dBm</p>
<p>4.6 TRP measured: (TRP is based on EIRP) This gives an idea about the directivity of the antenna.</p>	<p>dBm</p>
<p>3.10 TIS measured on RX1:</p>	<p>For RX1-SF12BW125 on 868.3MHz        dBm</p>
<p>3.11 TIS measured on RX2</p>	<p>For RX2-SF12BW125 on 869.525 MHz:        dBm</p>