

Supplementary information for EU Devices in the LoRaWAN® Showcase catalogue. Version 1.0

### Version of Questionnaire form from the Customer/ Device Manufacturer

Version	Date	Author	Update
1.0			Initial release from manufacture

### Supplementary Information on certified device

1 Supplementary information	
1.1 Manufacturer or Brand name	Hangzhou Laison Technology Co., Ltd.
1.2 Website	www.laisongroup.com
1.3 Sales / Marketing contact person, email:	clark.dai@laisontech.com
1.4 Technical contact person, email:	rufang.wang@laisontech.com
1.5 Commercial Product name	PARISE Smart Water Meter
1.6 Product code used when ordering / article number	LXSZ
1.7 Product Version : Hardware version: Firmware version:	LS450745 745 450
1.8 In what countries is the product available	World Widely
1.9 What date was / is the market introduction for this device / product?	2021-Oct
1.10 Is the device already working on a public LoRaWAN network.  If yes specify at which public operator, country and number of deployed devices on that network:	<input type="checkbox"/> Yes: <input checked="" type="checkbox"/> No
1.11 What functionality does the device provide and which sensor(s) does it contain?	Use case: Water meter metering and Billing. Smart Building  Short behavior description: Detect Water consumption
1.12 Accuracy & resolution for every sensor or measurement made by the device	
Name:	Reed
sensor accuracy (incl. unit): +/-	----
resolution (incl. unit):	0.1m <sup>3</sup>
measurement parameter:	Volume
measurement range	0m <sup>3</sup> -- 99999.9m <sup>3</sup>
Name:	Temperature Sensor

sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range	Typ ± *2°C 0.2 °C Temperature -40 ~ 85°C
Name: sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range	
Name: sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range	
Name: sensor accuracy (incl. unit): +/- resolution (incl. unit): measurement parameter: measurement range	
1.13 Uplinks are: <p style="text-align: right;">                     Periodic:                      Period:                      Explanation:                      Keep alive message period:                      Event triggered how:                 </p>	<input checked="" type="checkbox"/> <p>                     Once a day                      Upload daily measurement information                      Once a day                      Press the Button "Report" or Enter 2-digit token "43" via Infrared Comm.                 </p>
1.14 Parameter configuration of device (e.g. transmission or measurement interval, threshold levels, etc.)	<input checked="" type="checkbox"/> Remotely: <input checked="" type="checkbox"/> Over-the-air with LoRaWAN data downlinks <input checked="" type="checkbox"/> Specify if other: LoRa communication <input checked="" type="checkbox"/> Locally: <input type="checkbox"/> Via CLI: specify type of connector:  <input type="checkbox"/> Via NFC:  <input checked="" type="checkbox"/> Specify if other: Via Infrared
1.15 Does the application server send downlinks to the devices?	<input checked="" type="checkbox"/> Yes: (why/how often/typical size) Recharge ; if user recharged ; below 30 byte Set time ; if meter time error ; below 20 byte Read parameter ; if need maintain ; below 20 byte <input type="checkbox"/> No
1.16 Operating temperature of device - x °C to + x °C	Minimum -10 °C Maximum 80 °C
1.17 Is the payload structure available for decoding?	<input type="checkbox"/> Yes: <input checked="" type="checkbox"/> No Please attach the payload structure (+example of decoded payload)
1.18 Is there a decode-API available	<input type="checkbox"/> Yes: <input checked="" type="checkbox"/> No Please attach the API documentation
1.19 Is the firmware upgradeable and how?	<input checked="" type="checkbox"/> Yes: (how) Through UART or Infrared

<p>1.20 How can the device be reset to factory default settings?</p>	<p>Use Customization software and infrared tools.</p>
<p>1.21 How can the device be forced to re-initiate the join procedure?</p>	<p>Restart meter and report</p>
<p>1.22 Product certifications (IP rating, ATEX, ...)</p>	<p>1. IP rating: IP68 2. ATEX compliance: Other:</p>
<p>1.23 Which regulatory certifications are available (RED, CE, EMC)?</p>	<p><input type="checkbox"/> RED <input type="checkbox"/> CE <input type="checkbox"/> EMC Attach proof of certification to the mail in which this document is sent to a public operator</p>
<p>1.24 Power Supply</p>	<p><input type="checkbox"/> External power supply: Co4nnection: voltage: amperage:</p> <p><input checked="" type="checkbox"/> Internal battery: battery type: Lithium battery chemical composition: Li-SoCl<sub>2</sub> Battery self-discharge (%/year): &lt;2% Battery shelf life: 10 year capacity: 8500mAh weight: 87g rechargeable: <input type="checkbox"/> Yes: <input checked="" type="checkbox"/> No</p>
<p>1.25 Powering device on and off How is the device turned ON ? How is the device turned OFF ?</p>	<p>Report operation, Query operation; When there is no operation</p>
<p>1.26 Dimensions of device (Length x width x height)</p>	<p>19.5cm (L) x 9.25cm (W) x 13.6cm (H)</p>
<p>1.27 Weight of full device</p>	<p>1590g</p>
<p>1.28 Mounting of device 1. How to mount? 2. How to mount for best antenna propagation</p>	<p>1.The meter should be installed in horizontal position with register and LCD face upwards. The water flow direction in pipeline must be the same with the direction of arrow indicated on meter body. Please refer to installation instructions provided by LAISON for more information.</p> <p>2. Please install strictly according with the installation instructions provided by LAISON</p>

2 LoRaWAN Device Information

2.1 DevEUI Range (IEEE Compliance)	From : To :
2.2 LoRaWAN Class	<input checked="" type="checkbox"/> Class A <input type="checkbox"/> Class B <input type="checkbox"/> Class C
2.3 For Class C Device: Device Under Test restores previous RF settings at boot?	<input type="checkbox"/> Yes <input checked="" type="checkbox"/> No
2.4 In what LoRaWAN region/frequency ranges is the product available	<input checked="" type="checkbox"/> EU863-870 <input type="checkbox"/> US902-928 <input type="checkbox"/> AS923 <input checked="" type="checkbox"/> IN865-867 <input type="checkbox"/> KR920-923 <input type="checkbox"/> Other
2.5 Is the LoRaWAN test mode supported?	<input checked="" type="checkbox"/> Yes <input type="checkbox"/> No, why not
2.6 Tested and certified against which LoRaWAN Specification(s)	<input type="checkbox"/> V1.0 <input type="checkbox"/> V1.0.1 <input checked="" type="checkbox"/> V1.0.2 revB <input type="checkbox"/> V1.0.3 <input type="checkbox"/> V1.1.x <input type="checkbox"/> Other :
2.7 Link to document on the LoRa Alliance website	Link:
<p>2.8 Which TX power is used in production devices by default?</p> <p>- if LW 1.0.2 rev A or older is used:</p> <p>- if LW 1.0.2 rev B or newer is used</p>	<p><input type="checkbox"/> TXPower 0 (20dBm)  <input type="checkbox"/> TXPower 1 (14dBm)  <input type="checkbox"/> TXPower 2 (11dBm)  <input type="checkbox"/> TXPower 3 (8dBm)  <input type="checkbox"/> TXPower 4 (5dBm)  <input type="checkbox"/> TXPower 5 (2dBm)  <input type="checkbox"/> other TXPower (        dBm)</p> <p><input checked="" type="checkbox"/> TXPower 0 (MaxEIRP)  <input type="checkbox"/> TXPower 1 (MaxEIRP-2dB)  <input type="checkbox"/> TXPower 2 (MaxEIRP-4dB)  <input type="checkbox"/> TXPower 3 (MaxEIRP-6dB)  <input type="checkbox"/> TXPower 4 (MaxEIRP-8dB)  <input type="checkbox"/> TXPower 5 (MaxEIRP-10dB)  <input type="checkbox"/> TXPower 6 (MaxEIRP-12dB)  <input type="checkbox"/> TXPower 7 (MaxEIRP-14dB)</p> <p><input type="checkbox"/> other TXPower  (Max EIRP :        dB)</p>

<p>2.9 Which TX powers are supported by the device in production</p> <p>- if LW 1.0.2 rev A or older is used:</p>     <p>- if LW 1.0.2 rev B or newer is used</p>	<p><input type="checkbox"/> TXPower 0 (20dBm)</p> <p><input type="checkbox"/> TXPower 1 (14dBm)</p> <p><input type="checkbox"/> TXPower 2 (11dBm)</p> <p><input type="checkbox"/> TXPower 3 (8dBm)</p> <p><input type="checkbox"/> TXPower 4 (5dBm)</p> <p><input type="checkbox"/> TXPower 5 (2dBm)</p> <p><input type="checkbox"/> other TXPower (          dBm)</p> <p><input checked="" type="checkbox"/> TXPower 0 (MaxEIRP)</p> <p><input checked="" type="checkbox"/> TXPower 1 (MaxEIRP-2dB)</p> <p><input checked="" type="checkbox"/> TXPower 2 (MaxEIRP-4dB)</p> <p><input checked="" type="checkbox"/> TXPower 3 (MaxEIRP-6dB)</p> <p><input checked="" type="checkbox"/> TXPower 4 (MaxEIRP-8dB)</p> <p><input checked="" type="checkbox"/> TXPower 5 (MaxEIRP-10dB)</p> <p><input checked="" type="checkbox"/> TXPower 6 (MaxEIRP-12dB)</p> <p><input checked="" type="checkbox"/> TXPower 7 (MaxEIRP-14dB)</p> <p>(Max EIRP :          dB)</p>
<p>2.9 Which LoRaWAN Specification is currently supported on the production devices?</p>	<p><input type="checkbox"/> V1.0</p> <p><input type="checkbox"/> V1.0.1</p> <p><input type="checkbox"/> V1.0.2 revA</p> <p><input checked="" type="checkbox"/> V1.0.2 revB</p> <p><input type="checkbox"/> V1.0.4</p> <p><input type="checkbox"/> V1.1.x</p> <p><input type="checkbox"/> Other:</p>
<p>2.10 Will you re-certify your device when a new major LoRaWAN specification version is released</p>	<p><input type="checkbox"/> Yes.</p> <p><input checked="" type="checkbox"/> No, why : unconfirm</p>
<p>2.11 Has Interoperability prequalification testing been done?</p>	<p><input checked="" type="checkbox"/> Yes.</p> <p><input type="checkbox"/> No, why :</p> <p>Which Network Servers</p> <p><input type="checkbox"/> Actility</p> <p><input type="checkbox"/> Loriot</p> <p><input type="checkbox"/> TTI</p> <p><input checked="" type="checkbox"/> Other: Specify: RWC5020B Please attach all the test reports.</p>
<p>2.12 Is Activation Type OTAA the default</p>	<p><input checked="" type="checkbox"/> Yes.</p> <p><input type="checkbox"/> No, why :</p>
<p>2.13 For OTAA, is AppKey unique for each device?</p>	<p><input checked="" type="checkbox"/> Yes.</p> <p><input type="checkbox"/> No.</p>

<p>2.14 Is ADR implemented? Recommendation: ADR should always be activated. Exceptions can be made for moving devices but will need to be explained.</p>	<p><input checked="" type="checkbox"/> Activated <input type="checkbox"/> Deactivated, why :  <input checked="" type="checkbox"/> Configurable by user (recommendation: Activated by default) <input type="checkbox"/> Mixed, explain:</p>
<p>2.15 What values did you implement for: - ADR_ACK_LIMIT: - ADR_ACK_DELAY:</p>	<p>64 recommended value: 64 32 recommended value: 32</p>
<p>2.16 Do you use unconfirmed and/or confirmed uplinks and what is the data rate, timing and power back off algorithm?          Upon reception of a confirmed downlink message, is the next uplink sent immediately after the downlink ?Answers (radio buttons)</p>	<p><input checked="" type="checkbox"/> unconfirmed <input type="checkbox"/> confirmed, when and why: <input type="checkbox"/> Both, which is used when and why: Data rate, timing and power back-off algorithm (only if you use confirmed uplinks):          <input checked="" type="checkbox"/> Yes. <input type="checkbox"/> No, why :</p>
<p>2.17 Is the device doing a periodical rejoin? (only for OTAA)</p>	<p><input type="checkbox"/> Yes (frequency): <input checked="" type="checkbox"/> No. Why? How to trigger a rejoin? Three consecutive communication errors will re-join the network</p>
<p>2.18 Is the first join request sent on SF12?</p>	<p><input checked="" type="checkbox"/> Yes. <input type="checkbox"/> No, why: Explain the JoinRequest sequence if no JoinAccept is received - data rate, timing and power back-off algorithm.</p>
<p>2.19 On what SF and power setting is the first uplink (after join procedure) done?</p>	<p>SF: 10 TXPower: 0</p>
<p>2.20 Are you doing periodically reset of Uplink frame counter?</p>	<p><input type="checkbox"/> Yes (frequency/why): <input checked="" type="checkbox"/> No.</p>
<p>2.21 If LoRaWAN 1.0.x, DevNonce behaviour :</p>	<p><input checked="" type="checkbox"/> Based on a random value <input type="checkbox"/> Monotonically increasing never-wrapping counter</p>
<p>2.22 Uplink DataRate (0-7 supported)</p>	<p>Min: 0 Max: 7</p>
<p>2.23 RX1 Data Rate Offset</p>	<p><input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:</p>
<p>2.24 RX1 Delay</p>	<p><input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:</p>
<p>2.25 RX2 Data Rate</p>	<p><input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:</p>

2.26 RX2 Frequency	<input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:
2.27 RX1 Delay on JoinRequest (OTAA devices only)	<input checked="" type="checkbox"/> Default LoRaWAN in regards of ISM band <input type="checkbox"/> Other:
2.28 Mobility Profile (how your device moves)	<input checked="" type="checkbox"/> Near static <input type="checkbox"/> Walking speed <input type="checkbox"/> Vehicle speed <input type="checkbox"/> Random
2.29 Frame Counters Up To 32-bits	<input checked="" type="checkbox"/> Frame counter-up <input type="checkbox"/> Frame counter-down
2.30 Which MAC commands does the device support	<input checked="" type="checkbox"/> LinkCheckReq / LinkCheckAns <input checked="" type="checkbox"/> TXParamSetupReq / TXParamSetupAns <input checked="" type="checkbox"/> LinkADRReq / LinkADRAns <input type="checkbox"/> DutyCycleReq / DutyCycleAns <input checked="" type="checkbox"/> RXParamSetupReq /RXParamSetupAns <input checked="" type="checkbox"/> DevStatusReq / DevStatusAns <input checked="" type="checkbox"/> NewChannelReq / NewChannelAns <input checked="" type="checkbox"/> TXTimingSetupReq / TXTimingSetupAns
2.31 LoRaWAN Stack Type (optional)	<input type="checkbox"/> Semtech/Stackforce <input checked="" type="checkbox"/> Semtech/Stackforce with modifications <input type="checkbox"/> IBM <input type="checkbox"/> IBM with modifications <input type="checkbox"/> Proprietary- Other, name it:
2.32 LoRaWAN Stack Version (optional)	V1.0.2
2.33 LoRa Radio Hardware (optional)	<input checked="" type="checkbox"/> Proprietary: SX chip used: SX1276 <input type="checkbox"/> LoRaWAN Modem/Module: Manufacturer: Part Number: Firmware revision:
2.34 Multicast support (optional)	<input type="checkbox"/> Yes: Multicast DevAddr: Multicast AppSKey: Multicast NwkSKey: Payload: Port: <input checked="" type="checkbox"/> No.

**3 Radio Frequency Information**

<p>3.1 Type of Antenna</p>	<p><input checked="" type="checkbox"/>Wire  <input type="checkbox"/>PCB  <input type="checkbox"/>External  <input type="checkbox"/>Other: (which type)</p>
<p>3.2 Antenna gain [dBi or dBd]</p>	<p>2 dBi or dBd</p>
<p>3.3 Did you measure and take into account the loss between the modem and the antenna?</p>	<p><input type="checkbox"/>Yes, -10 dB loss  <input checked="" type="checkbox"/>No, why:</p>
<p>3.4 For LW 1.0.2 rev A or older devices: which TXPower setting should be used on the network for your device*:</p>	<p><input type="checkbox"/>TXPower 0 (20dBm)  <input type="checkbox"/>TXPower 1 (14dBm)  <input type="checkbox"/>TXPower 2 (11dBm)  <input type="checkbox"/>TXPower 3 (8dBm)  <input type="checkbox"/>TXPower 4 (5dBm)  <input type="checkbox"/>TXPower 5 (2dBm)  <input type="checkbox"/>other txpower (        dBm)</p>
<p>3.5 Did you calibrate your device with the antenna gain and measured loss in between the chipset and antenna? This so that your device emits with maximal power when using TXPower 1 for LW 1.0.2 rev A or older devices (= 14dBm) and TXPower 0 for LW 1.0.2 rev B or newer devices (= MaxEIRP or 16.15dBm EIRP)*.</p>	<p><input type="checkbox"/>Yes,        dB loss  <input checked="" type="checkbox"/>No, why: We directly test whether the final output signal strength of the equipment reaches the standard as a factory test</p>



**4 Battery and TX Power Information**

Please indicate if you do not want Section 4 displayed on the LoRa Alliance Website  Yes  
 If yes please supply contact details for the operators to request the information for Section 4

<p>4.1 Battery consumption of the device (including modem, sensors and all other electronics)</p>	<p>TX current: 100mA                  RX current: 10 mA                  Idle time current: 0.03mA</p>																																				
<p>4.2 Estimated battery life in years based on the number of transmissions (including sensor readings) at SF7, SF10 &amp; SF12 with your battery self-discharge and aging over time taken into account.</p> <p><b>Assumptions:</b></p> <ul style="list-style-type: none"> <li>- Product shelf life before use: Maximum 1 year.</li> <li>- At an environment temperature of 20°C.</li> <li>- LoRaWAN specification used for battery life calculation:</li> <li>- TX power setting (txpower) used for battery life calculation:</li> <li>- Payload size used for battery life calculation (should be average payload size of production device):</li> <li>- Additional assumptions or comments on battery life (Typical usage</li> </ul>	<table border="1"> <thead> <tr> <th colspan="4">Battery life in years</th> </tr> <tr> <th>Transmission Periodicity (transmissions/day)</th> <th>SF7</th> <th>SF10</th> <th>SF12</th> </tr> </thead> <tbody> <tr> <td>144</td> <td></td> <td></td> <td></td> </tr> <tr> <td>96</td> <td>8</td> <td>8</td> <td>8</td> </tr> <tr> <td>48</td> <td>10</td> <td>10</td> <td>10</td> </tr> <tr> <td>24</td> <td></td> <td></td> <td></td> </tr> <tr> <td>12</td> <td></td> <td></td> <td></td> </tr> <tr> <td>4</td> <td></td> <td></td> <td></td> </tr> <tr> <td>1</td> <td></td> <td></td> <td></td> </tr> </tbody> </table> <p><input type="checkbox"/> LW1.0.1  <input type="checkbox"/> LW1.0.2 revA  <input checked="" type="checkbox"/> LW1.0.2 revB  <input type="checkbox"/> Other :</p> <p><input type="checkbox"/> LW1.0.1  <input type="checkbox"/> LW1.0.2 revA  <input checked="" type="checkbox"/> LW1.0.2 revB  <input type="checkbox"/> Other :</p> <p>70 bytes</p> <p>Switch valve</p>	Battery life in years				Transmission Periodicity (transmissions/day)	SF7	SF10	SF12	144				96	8	8	8	48	10	10	10	24				12				4				1			
Battery life in years																																					
Transmission Periodicity (transmissions/day)	SF7	SF10	SF12																																		
144																																					
96	8	8	8																																		
48	10	10	10																																		
24																																					
12																																					
4																																					
1																																					

<p>4.3 Which TX power setting (TXPower) was used in the RF test?</p> <p>- If LW 1.0.2 rev A or older device:</p> <p>- If LW 1.0.2 rev B or newer device:</p>	<p><input type="checkbox"/> TXPower 0 (20dBm)  <input type="checkbox"/> TXPower 1 (14dBm)  <input type="checkbox"/> TXPower 2 (11dBm)  <input type="checkbox"/> TXPower 3 (8dBm)  <input type="checkbox"/> TXPower 4 (5dBm)  <input type="checkbox"/> TXPower 5 (2dBm)  <input type="checkbox"/> other TXPower (          dBm)</p> <p><input checked="" type="checkbox"/> TXPower 0 (MaxEIRP)  <input type="checkbox"/> TXPower 1 (MaxEIRP-2dB)  <input type="checkbox"/> TXPower 2 (MaxEIRP-4dB)  <input type="checkbox"/> TXPower 3 (MaxEIRP-6dB)  <input type="checkbox"/> TXPower 4 (MaxEIRP-8dB)  <input type="checkbox"/> TXPower 5 (MaxEIRP-10dB)  <input type="checkbox"/> TXPower 6 (MaxEIRP-12dB)  <input type="checkbox"/> TXPower 7 (MaxEIRP-14dB)  <input type="checkbox"/> other TXPower  (MaxEIRP-          dBdBm)</p>
<p>4.4 Is this the same TX power setting (TXPower) used by default in production devices (before network ADR)?</p>	<p><input checked="" type="checkbox"/> Yes,  <input type="checkbox"/> No, why:</p>
<p>4.5 Maximum ERP measured: (ERP = EIRP - 2.15 dB; LoRaWAN allows 14 dBm ERP)</p>	<p>        dBm</p>
<p>4.6 TRP measured: (TRP is based on EIRP)  This gives an idea about the directivity of the antenna.</p>	<p>        dBm</p>
<p>3.10 TIS measured on RX1:</p>	<p>For RX1-SF12BW125 on 868.3MHz          dBm</p>
<p>3.11 TIS measured on RX2</p>	<p>For RX2-SF12BW125 on 869.525 MHz:          dBm</p>